

Find Me 0 (Trim/No Trim)

Designed by Jorge Herrera

LED - Power LED - 3W - 170lm - 2700K - CRI> 90 - Beam° 26

Recessed adjustable luminaire for indoor application. Remote power supply 250 mA not included.



Are you a professional and your project needs consulting and support?



BOOK AN APPOINTMENT

Main specifications

Mounting	Ceiling recessed
Environments	Indoor dry location
Light source type	LED
Light sources included	Yes
LED type	Power LED
Lamp category	LED
Number of lamps	1
Power (W)	3
Source flux (lm)	300
Lumen Output (lm)	170

Physical

Colour	Black
Orientation	Adjustable
Rotation (°)	360
Longitudinal tilting (°)	90
Recessed depth (mm)	135
Spot diameter (mm)	24
Net weight (kg)	0.14
IP internal	20



Download

Mounting instructions [Download PDF](#)

Photometric Files

LDT / IES [Download ZIP](#)

Technical Drawings

2D [Download ZIP](#)


3D [Download ZIP](#)



Ecodesign and Energy Labelling



Schematic light drawing



Photometric

Lighting type	Direct
Light distribution	Symmetric
CCT (K)	2700
CRI>	90
Rf fidelity index	91
Rg gamut index	98
LED Life / Failure Ratio	L80B20 >36000h (Tc=85°C)
Beam angle C0-180 (°)	26
Beam angle C90-270 (°)	26
UGRL	<10

Electrical

Insulation class	III
Frequency (Hz)	0
Forward voltage (V)	12
LED current (mA)	250
Power supply	Remote excluded
Dimmable	Yes
Power supply type	Non Dimmable, Dimmable Casambi, Mains Cut Dimming, Dimmable 0-10V, Dimmable DALI 2

Notes

Accessories included (honeycomb and screening crosspiece). Remote power supply to be installed in an accessible place. It is not recommended to use dimmable drivers of several brands due to the specific dimming curves of each brand. To use only one driver for various spots, connect the spots in series.

Accessories & Power Supply



REQUIRED
Control interface

ACCESSORYTYPE1

60.9392
Casambi controller. Requires 1-10V or Dali driver. It must be ordered separately

REQUIRED
Power supply

ACCESSORYTYPE1

60.9405
Constant voltage supply source of 20W, 100-240V - 50/60Hz with adjustable 250 mA supply voltage. Dimmable 0-10V

REQUIRED
Power supply


ACCESSORYTYPE1

60.9160
Non dimmable continuous current power supply of 220/240V - 50/60Hz with power current selected through adjustable with switch 200 mA - 8,5W / 250mA - 11W / 300 mA - 13W / 350 mA - 15W / 400 mA - 17,5W / 450 mA - 19,5W / 500 mA - 22W

REQUIRED
Power supply

ACCESSORYTYPE1

60.9601
Constant voltage supply source of 20W, 100-240V - 50/60Hz with adjustable 250 mA supply voltage. Dimmable DALI



REQUIRED
Power supply

ACCESSORYTYPE1

60.9744
Constant voltage supply source of 10W, 100-240V - 50/60Hz with non adjustable 250 mA supply voltage

REQUIRED
Power supply

ACCESSORYTYPE1

60.9949
Continuous current power supply of 7,2-24W, 220/240V - 50/60Hz with power current selected through adjustable switch. 200mA - 8W / 250mA - 10W / 300mA - 12W / 350mA - 14W. Trailing & leading edge, mains dimming.