

Find Me 1 Broadcast

Designed by Jorge Herrera, 2026



LED accent lighting module for installation in the The Micro Running Magnet Pro system. Integrated DC/DC electronic converter. Broadcast version, with simultaneous control of all luminaires.

Are you a professional and your project needs consulting and support?


[BOOK AN APPOINTMENT](#)

Main specifications

Mounting	Track
Environments	Indoor dry location
Light source type	LED
Light sources included	Yes
LED type	Power LED
Number of lamps	1
Power (W)	5.5
Source flux (lm)	480
Lumen Output (lm)	385

Physical

Colour	White
Orientation	Adjustable
Rotation (°)	360
Longitudinal tilting (°)	90
Spot diameter (mm)	33
Length (mm)	41
Net weight (kg)	0.11
IP internal	20



Download

Mounting instructions [↓ PDF](#)

Photometric Files

LDT / IES [↓ ZIP](#)

Technical Drawings


2D [↓ ZIP](#)

3D [↓ ZIP](#)




Ecodesign and Energy Labelling

This product contains a light source of energy efficiency class F



Replaceable (LED only) light source by a professional

Schematic light drawing



Photometric

Lighting type	Direct
Light distribution	Symmetric
CCT (K)	4000
CRI>	90
McAdam steps (SDCM)	3
Rf fidelity index	91
Rg gamut index	98
LED Life / Failure Ratio	L95B11 > 50.000h (Tc=85°C)
Beam angle C0-180 (°)	20
Beam angle C90-270 (°)	20
Extreme cut off	No
UGR _L	<10

Electrical

Insulation class	III
Forward voltage (V)	24
Power supply	Remote excluded
Dimmable	Yes
Dimming range (%)	1-100

Notes

Accessories included (honeycomb and screening crosspiece). The control system for the Casambi version of the light fixtures is directly and individually regulated wirelessly using the FLOS Control® powered by Casambi application. Other types of regulation operate in broadcast mode (all lights are regulated at the same time). The Casambi module is integrated within the fixture and works with a 24V non-dimmable power supply connected directly to the track.