

My Spot Ø35 Short Recessed

Designed by FLOS Architectural, 2024




LED - LED array - 7.4W - 599lm - 3000K - CRI> 90 - Beam° 20

LED lighting module for recessed applications. Optical with double focal lens technology, low glare and high visual comfort. Adjustable by tilting and turning. In the downlight position, the connector arm is perfectly flush with the product.

Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT



Main specifications

Mounting	Recessed
LED type	LED array
Lamp category	LED
Number of lamps	1
Power (W)	7.4
System power (W)	9.4
Source flux (lm)	711
Lumen Output (lm)	599

Physical

Colour	Brushed Steel
Rotation (°)	360
Longitudinal tilting (°)	90
Recessed depth (mm)	50
Net weight (kg)	0.57
IP internal	20
IP external	20

Download

Mounting instructions [↓ PDF](#)

Photometric Files

LDT / IES [↓ ZIP](#)

Technical Drawings

2D [↓ ZIP](#)

3D [↓ ZIP](#)




Ecodesign and Energy Labelling

 Non-replaceable light source

 Replaceable control gear by a professional

Schematic light drawing



Photometric

Lighting type	Direct
Light distribution	Symmetric
CCT (K)	3000
CRI>	90
McAdam steps (SDCM)	2
Rf fidelity index	90
Rg gamut index	100
LED Life / Failure Ratio	L90B50>50.000h_Tc85°C
Beam angle C0-180 (°)	20
Beam angle C90-270 (°)	20
Extreme cut off	No
UGR _L	<10

Electrical

Insulation class	III
Forward voltage (V)	18
LED current (mA)	400
Power supply	Remote
Dimmable	Yes
Power supply type	Non Dimmable, Dimmable Casambi, Mains Cut Dimming, Dimmable DALI 2, Dimmable 1-10V, Dimmable Push
Batteries inside	No

Accessories & Power Supply



REQUIRED
Power supply

Electrical

60.7773

Constant current power supply
28W, 220-240V - 50/60Hz with
programmable output current via
DIP switch. 100mA - 5.4W /
150mA - 7.9W / 200mA - 10.4W /
250mA - 13W / 300mA - 15.5W /
350mA - 18W / 400mA - 20.4W /
450mA - 23W / 500mA - 25.8W /
550mA - 28.4W...

REQUIRED
Power supply

Electrical

60.9208

Continuous current power supply
of 13-20W - Dim 1-10V&Push -
110/240V - 50/60Hz with power
current selected through
adjustable

REQUIRED
Power supply

Electrical

60.7774

Constant current power supply
20W, 220-240V - 50/60Hz with
programmable output current via
DIP switch. 100mA - 5.8W /
150mA - 8.3W / 200mA - 10.8W /
250mA - 13.2W / 300mA - 15.6W /
350mA - 18.1W / 400mA - 20.6W /
450mA - 23W / 500mA - 22.9W /
550mA - 2...

REQUIRED
Power supply

Electrical

60.7661

Constant current power supply
15W, 220-240V - 50/60Hz with
programmable output current via
DIP switch. 400mA - 11.6W /
450mA - 13W / 500mA - 14.5W /
550mA - 15.9W. Phase-cut
dimmable (Triac).



REQUIRED
Power supply

Electrical

60.7785

Constant current power supply
42W, 220-240V CASAMBI
dimmable.