



F004B31AU56 Matte Stainless Steel

Landlord Ground Ø64 Non Dimmable Matt **Stainless Steel**

Designed by Piero Lissoni, 2018



24V remote power supply to be ordered separately. Necessary box for installation, to be ordered separately.

Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT



Main specifications

EAN	8054793194820	
Mounting	In-ground	
Environments	Outdoor wet location	
Light Source Type	LED	
Light sources included	Yes	
LED type	Power LED	
Number of lamps	1	
Power (W)	3	
System flux (lm)	189	

Physical

Color	Matte Stainless Steel
Orientation	Fixed
Net weight (lb)	0.75
Package height (in)	5.28
Package width (in)	2.76
Package length (in)	3.27
Package volume (in)	47.54
IP internal	67
IP external	66

Download

owinoda		
amily spec sheet	$\underline{\bot}$	ZI
lounting instructions	$\overline{\bot}$	ZI

Photometric Files

LDT / IES







Ecodesign and Energy Labelling

This product contains a light source of energy efficiency class E




Replaceable (LED only) light source by a professional

https://professional.flos.com/en-US/us/product/landlord-ground-64-non-dimmable-matt-stainless-steel-f004b31au56/

F004B31AU56

Schematic light drawing



Bear	Beam Angle:	
h(m)	E(lx)	D(m)
1	1960	0.27
2	490	0.53
3	218	0.80
4	122	1.06
5	78	1.33

Photometric

Light distribution	Symmetric
CCT (K)	3000
CRI>	80
Beam angle C0-180 (°)	15
Beam angle C90-270 (°)	15

Electrical

Main voltage (Vac)	24
Driver	Remote excluded
Dimmable	Yes
Dimming interface	Remote Dimmable (Dimmer Not Included)

Notes

Carefully install and maintain the fixtures to avoid damaging the coating. For LED fixtures, most problems are tied to electrical issues related to the insulation, which may cause destructive electrical discharges. These are frequently caused by:

- power surges from the power network where fixture is connected.
- electrostatic discharge (ESD) from the environment.

We recommend installing a power-surge protection device on the fixture to reduce the intensity of these effects and prevent irreversible damages. The specific device should be chosen based on the electrical characteristics.

Accessories & Power Supply



REQUIRED Accessory

F004Z0K0000

Box for installation