

Continuous current supply source of 220-240V - 50/60Hz - 300mA 15W with dimmable Casambi

Continuous current supply source of 240V - 50/60Hz with dimmable Casambi 300 mA - 18W



Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT


Main specifications

Environments	Indoor dry location
Light sources included	No
Power (W)	18

Physical

IP internal	20
-------------	----

Ecodesign and Energy Labelling



Replaceable control gear by a professional



Photometric

Extreme cut off No

Electrical

Insulation class	II
Frequency (Hz)	50/60
Main voltage (Vac)	220-240
Driver output voltage (V)	10-36
Forward voltage (V)	36
LED current (mA)	300
Power supply	Remote
Dimmable	Yes
Power supply type	Dimmable Casambi
Dimming range (%)	1-100
Dimming interface	Remote Dimmable (Dimmer Not Included)
Emergency	Yes
Batteries inside	No