

Continuous current supply source of 220-240V - 50/60Hz - 300mA.with dimmable Dali 2

Continuous current supply source of 240V - 50/60Hz with dimmable Dali 2 300 mA - 25W



Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT


Main specifications

Light sources included	No
Power (W)	25

Physical

Net weight (kg)	0.1
IP internal	20

Ecodesign and Energy Labelling



Replaceable control gear by a professional



Photometric

Extreme cut off No

Electrical

Insulation class	II
Frequency (Hz)	50/60
Main voltage (Vac)	220-240
Driver output voltage (V)	6-50
Forward voltage (V)	50
LED current (mA)	300
Power supply	Remote
Dimmable	Yes
Power supply type	Dimmable DALI 2
Dimming range (%)	1-100
Dimming interface	Remote Dimmable (Dimmer Not Included)
Emergency	Yes
Batteries inside	No