

FLOS

FU333109 White

Glo-Ball Basic Zero Switch

Designed by Jasper Morrison, 2009




Halogen - 40W

Part of the popular Glo-Ball Series, the Glo-Ball Basic Zero was created in 1998 by artist Jasper Morrison to invoke the radiant calm of a full moon. This unique table lamp has a white acid-etched glass diffuser and a base that is 30% fiberglass reinforced injection-molded polyamide (UL-94 V2). The die-cast aluminum diffuser support is painted gray. Inspiration behind the design: Inspired by the soft and serene glow of a full moon in a clear sky, Jasper Morrison created the Glo Ball series to illuminate the otherworldly magic of the night.

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)



Main specifications

EAN	8059607029046
Mounting	Table
Environments	Indoor dry location
Light Source Type	Bulb
Light sources included	No
Lamp category	Halogen
Lamp type	T4
Lamp holders	G9
Number of lamps	1
Power (W)	40

Physical

Color	White
Length (in)	7.48
Cord color	Black
Cord length (in)	74.803
Net weight (lb)	1.98
Gross weight (lb)	3.31
Package height (in)	8.86
Package width (in)	10.24
Package length (in)	10.63
Package volume (in)	963.87
IP internal	40

Download

[Mounting instructions](#)



Photometric

Lighting type	Total
Light distribution	Roto symmetric
Extreme cut off	No

Electrical

Insulation class	II
Frequency (Hz)	60
Main voltage (Vac)	120
Dimmable	Yes
Dimming interface	Switch Integrated (Remote Dimmable)
Plug type	Type A
Batteries inside	No

Bulbs





NOT INCLUDED

RF34658

60W G9 Frosted Halogen Lamp

Spare Parts



- | | | |
|-----|---|-----------|
| 01. | Glo-Ball Ceiling/Wall/Basic Zero
diffuser assembly | RF3335100 |
| 02. | G9 lamp holder assembly | RFU333100 |
| 03. | Glo-Ball Basic Zero swt US
electrical mounting with on/off
switch | RF21321 |



RF3335100
Glo-Ball Ceiling/Wall/Basic Zero
diffuser assembly



RFU333100
G9 lamp holder assembly



RF21321
Glo-Ball Basic Zero swt US
electrical mounting with on/off
switch