

FLOS

60.9957.0500


Continuous current supply source of 220-240V - 50/60Hz - 500mA.with dimmable Dali 2



Continuous current supply source of 240V - 50/60Hz with dimmable Dali 2 500 mA - 25W

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)



Main specifications

Light sources included No

Power (W) 25


Physical

Net weight (kg) 0.1

IP internal 20



Ecodesign and Energy Labelling



Replaceable control gear by a professional

Electrical

Insulation class	II
Frequency (Hz)	50/60
Main voltage (Vac)	220-240
Driver output voltage (V)	6-50
Forward voltage (V)	50
LED current (mA)	500
Power supply	Remote
Dimmable	Yes
Power supply type	Dimmable DALI 2
Dimming range (%)	1-100
Dimming interface	Remote Dimmable (Dimmer Not Included)
Emergency	Yes
Batteries inside	No