

60.7963

Power Supply & Casambi Controler 220-240V.40W. 300 mA a 1050 mA output current set via DIP switch.

Adjustable constant-current power supply from 300 mA to 1050 mA, with a power rating of 42 W and a 220–240 V, 50–60 Hz input. Output current is set via DIP switch. Casambi dimmable.



Are you a professional and your project needs consulting and support?


BOOK AN APPOINTMENT

Main specifications

Environments	Indoor dry location
Power (W)	20

Physical

Net weight (kg)	0.13
IP internal	20




Photometric

Extreme cut off	No
-----------------	----

Electrical

Insulation class	II
Main voltage (Vac)	220-240
LED current (mA)	300-1050
Power supply	Remote
Dimmable	Yes
Power supply type	Dimmable Casambi
Dimming interface	Remote Dimmable (Dimmer Not Included)

Ecodesign and Energy Labelling



Replaceable control gear by a professional