


FLOS

 FU041630 Black

Arrangements Small Rose

Designed by Michael Anastassiades, 2018



Only canopy for Flos Arrangements. Please use the Arrangements configurator to build your own custom creation. Arrangements is a modular system of geometric light elements that can be combined in different ways, creating multiple compositions into individual chandeliers. Each unit simply attaches onto the previous one as if resting, balancing perfectly as a part of a glowing chain. Please note that the maximum power is 190 watts. You can choose any combination with the caveat that there can only be one or broken line and when you attach it, it must go at the bottom. This is an embedded canopy with two sizes. The first size is Max 70 watts and the second is 190 watts. Your purchase will automatically choose the appropriate canopy based on the watts necessary for your fixture. Please use the configurator to build your own custom creation

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)

Download

Mounting instructions




Main specifications

| | |
|--------------|---------------------|
| EAN | 8059607075678 |
| Mounting | Suspension |
| Environments | Indoor dry location |
| Power (W) | 78 |

Physical

| | |
|-----------------------------|--------|
| Color | Black |
| Cord color | Black |
| Cord length (in) | 94.488 |
| Canopy color | Black |
| Canopy length/diameter (in) | 5.906 |
| Canopy height (in) | 2.756 |
| Net weight (lb) | 2.76 |
| Package height (in) | 9.45 |
| Package width (in) | 4.72 |
| Package length (in) | 10.24 |
| Package volume (in) | 456.95 |

Ecodesign and Energy Labelling



Replaceable control gear by a professional



Photometric

Extreme cut off No

Electrical

| | |
|--------------------|---|
| Frequency (Hz) | 50/60 |
| Main voltage (Vac) | 120-277 |
| Driver | Integrated |
| Dimmable | Yes |
| Dimming type | Dimmable 0-10V, Dimmable Push, Dimmable 1-10V, Dimmable DALI 1 |
| Dimming interface | Remote Dimmable (Dimmer Not Included) |

Spare Parts



| | | |
|-----|--|-----------|
| 01. | Stretch cable ceiling rose kit | RF0410400 |
| 02. | Led dimmer kit | RF35452 |
| 05. | Power supply kit for Arrangements small & Noctambule | RF0410500 |
| 08. | Arrangements Small ceiling rose cover | RF0410700 |
| 09. | Spacers cable | RF26602 |
| 10. | Regolation cables key | RF26440 |
| 11. | Element support assembly | RF26906 |



RF0410400

Stretch cable ceiling rose kit



RF35452

Led dimmer kit



RF0410500

Power supply kit for
Arrangements small &
Noctambule



RF0410700

Arrangements Small ceiling rose
cover



RF26602

Spacers cable



RF26440

Regulation cables key



RF26906

Element support assembly