

## Kap Ø 105 Fixed Optic Flood

Designed by FLOS Architectural, 2019

LED - LED array - 22.8W - 1815lm - 2700K - CRI> 90 - Beam° 51



Recessed luminaire with LED light source. Remote transformer not included. Pre-installation frame. To be ordered separately. Diffusing lens included.

Are you a professional and your project needs consulting and support?


BOOK AN APPOINTMENT

## Main specifications

Mounting	Ceiling recessed
Environments	Indoor dry location
Light Source Type	LED
LED type	LED array
Lamp category	LED
Ilcos	No
Bulb finish	Clear
Number of heads	1
Power (W)	22.8
System power (W)	25.9
Source flux (lm)	2085
System flux (lm)	1815
Efficacy (lm/W)	70

### Physical

Colour	White
Trim	No
Orientation	Fixed
Recessed depth (mm)	150
Spot diameter (mm)	105
Net weight (kg)	0.48
Package height (mm)	190
Package width (mm)	175
Package length (mm)	220
IP internal	20
IP external	54





## Download

Mounting instructions



#### Photometric Files

LDT / IES



## **Technical Drawings**

2D	<b>↓</b> ZIP
3D	<b>⊥</b> ZIP
<b>a</b> Bim	<b>↓</b> ZIP

















https://professional.flos.com/en/global/product/kap-105-fixed-optic-flood-05.7102.b1/

05.7102.B1

## Schematic light drawing



Beam Angle:		51°
h(m)	) E(lx)	D(m)
1_	2755	0.96
2	689	1.91
3	306	2.87
4	172	3.82
5	110	4.78

30° / 2755 cd / 30°	5
_uminous flux luminaire	
101E les COMPENS OUT OFF	

# **Ecodesign and Energy** Labelling



Replaceable (LED only) light source by a professional



Replaceable control gear by a professional

#### Photometric

Lighting type	Direct
Light distribution	Symmetric
CCT (K)	2700
CRI>	90
McAdam steps (SDCM)	3
LED Life / Failure Ratio	L80B50
Beam angle C0-180 (°)	51
Beam angle C90-270 (°)	51
UGR <sub>L</sub>	20

#### Electrical

Insulation class	III
Frequency (Hz)	0
Main voltage (Vac)	34
Forward voltage (V)	34
LED current (mA)	650
Driver	Remote excluded
Dimmable	Yes
Dimming type	Non Dimmable, Dimmable DALI 2, Dimmable Casambi, Dimmable 1-10V
Emergency type	No

#### Accessories & Power Supply





REQUIRED Frame

Installation

Installation frame No Trim



**REQUIRED** Power supply

Electrical

Continuous current power supply, dimmable Casambi, 220/240V - 50/60Hz, 300mA -16W / 350mA - 18,5W / 400mA -21,5W / 450 mA - 24W / 500mA -27W / 600mA - 32W / 650 mA -35W / 700 mA - 36W /750 /800 /900 /1000 /1050 /1200 mA -38W.



REQUIRED Power supply

Electrical

Continuous current power supply, 0/1-10V dimmable, 220/240V - 50/60Hz, 300mA-16W / 350mA-18W / 400mA-21W / 500mA-27W / 600mA-32W / 650mA-35W /700 /750 /800 /900/ 950/ 1000 /1050mA-36W



REQUIRED Power supply

Electrical

Continuous current supply source of 240V - 50/60Hz with dimmable Dali 2, push dimming. 300mA - 16W / 350mA - 18W / 400mA - 21W / 500mA - 27W / 600mA - 32W / 650 mA - 35W / 700 / 750 / 800 / 900 / 1000 / 1050 mA - 36W



REQUIRED Power supply

Electrical



30W, 220-240V - 50/60Hz with dip-switch programmable power supply current.



REQUIRED Power supply

Electrical

Constant current power supply,

Non dimmable continuous current power supply. 15-30W, 220/240V -50/60Hz with power current selected through adjustable switch. 350mA - 15W / 400mA - 17W / 450mA - 19W / 500mA - 22W / 550mA - 24W / 600mA - 26W / 650mA - 28W / 700mA - 30W.